How to add DS-K1T502DBWX-C to NVR

Purpose:

Get liveview or record the video from DS-K1T502DBWX-C on NVR.

Device List: DS-K1T502DBWX-C V1.7.1 220719 DS-9664NI-I16 V4.61.020 build 220708

Steps:

1. Login NVR web configuration page, and go to Configuration-> Camera Management-> IP Camera-> Custom Protocol, Single Click

HIKVISION	Live	/iew	Playba	:k file A	pplication C	Configuration				🛃 Download Plu	g-in 💄 admin 🕦 I	Help 🕒 Logo
🖵 Local		IP C	amera	More Configure								
🖺 System	^	+ A	dd 🔟 D	elete + Quick Add	🖹 Custom P	rotocol 🔅 Activate	∠ Upgrade					
System Settings			Chann	Camera Name	IP Address	Channel No.	Management Port	Security	Status	Protocol	Connect	Opera
Maintenance			D1	IPCamera 01	10.7.68.13	1	554	Weak	Online	HIKVSION_RTSP	http://10.7.68.1	Ľ
			D2	IPCamera 02	10.7.68.13	1	80	Weak	Offline(Conn	ONVIF	http://10.9.96.8	Ľ
	t											
Camera Managerr	nent											
Live View Settings	5											

2. Input the custom protocol name and corresponding information as below in the pop up menu:

Custom Protocol					
	1 ~	Custom Protocol	1	~	
* Protocol Name	HIKVSION_RTSP	* Protocol Name	HIKVSION_RTSP		
	HIKVSION DAHUA			HUA) (UNIVIEW
	TPLINK HUAWEI		TPLINK HU	AWEI	
	Main Stream Sut >		< sam Sub-Str	eam	
Enable Stream		Enable Stream			
Protocol	RTSP ~	Protocol	RTSP	~	
Transfer Protocol	Auto ~	Transfer Protocol	Auto	~	
*Port	554	* Port	554		
Stream Path	ch1/main/av_stream	Stream Path	ch1/sub/av_stream		
RTSP Example [Ty]	pe]://[IP Address]:[Port]/[Path]	RTSP Example:[Ty	pe]://[IP Address]:[Port]/[P	'ath]	
rtsp://192.168.0.1;5	54/ch1/main/av_stream	rtsp://192.168.0.1.3	554/ch1/main/av_stream		
			_	_	

3. Back to the IP camera page, click Add and select the custom protocol HIKVISIH-RTSP and input the corresponding information, click OK

l	L				<u> </u>		1			Ľ	L	Ľ	L	Ľ	L	Ľ												<u> </u>	-		_		 	ran		- 14	vy	<i>,</i>		'				_	٢,
	×	×	×	×	×	×	×	K	<			1	1	1	1																														
us Proto												1	5	ł	ł	tu	US	US	s					F	Pr	ro	to	00	0	4				C	201	n	ne	ect	1			C	p	era	
nline HIKV	r		~	~]									5	2	×	n	nli	lir	ine	e			2	HI	IK	(19	SIG	0	N			h	ittç	p:)	//1	10	0.9						
nline HIKV														5	2	×	20	nli	lir	ine	e			ł	H	IK	2	19	SIG	0	N			h	ttp	p:/	//1	10	0.9	ə					
												l	I	ł	I																														
	P		Ŗ	P								l	l	l	I																														
	Þ		Ð	P								l		l	I																														
												l	I	ł	I																														
												l	l	l	I																														
												l		l	I																														
											ł	ł	l	ł	I																														
			ł	4							1	١	I	l	l																														
			4	4]																<				1				>			1	1					/1				G

4. When the status shows online, you can get LiveView or set recording schedule for this channel



Test on 26-Sep 2022